

## How to update:

Do not plug Flash-drive to the receiver simultaneously with the Software update and the Database updates! (if the Flash-file storage will have simultaneously Software and Database updates, then only Software will be updated)

Do not turn the power off during the upgrade Software and Database!

Previous session with USB Flash-drive in the personal computer must be correctly finished!

Flash-drive must fully comply with USB 2.0 specifications and have a FAT32 filesystem!

### ***For versions prior to 1.0.26 inclusive:***

1. Insert the USB Flash-drive with Software update (file HD9300-XXXX.upg) into the receiver's USB port. A message on the available Software update appears.
2. Select "Yes" and then click OK.
3. Receiver will download the Software from Flash-drive and start the upgrade process.
4. Wait for the front panel of the symbols «b-YY», where YY - the percentage of Software upgrade process.
5. Remove Flash-drive from the USB port, without waiting for the upgrade process finished!
6. After updating, receiver will automatically reboot with the new Software version.
7. Insert the USB Flash-drive with the Database update(file DBHD9300-XXXX.upg) into the receiver's USB port. A message on the available Database upgrade appears.
8. Select "Yes" and then click OK.
9. Receiver will download the Database from Flash-drive and start the upgrade process.
10. Wait for the front of the symbols «b-YY», where YY - the percentage of Database upgrade process.
11. Remove Flash-drive from the USB port, without waiting for the upgrade process finished!
12. After updating, receiver will automatically reboot with the new Database version.

### ***For versions since 1.0.27:***

1. Insert the USB Flash-drive with Software update (file HD9300-XXXX.upg) into the receiver's USB port. A message on the available Software update appears.
2. Select "Yes" and then click OK.
3. Receiver will download the Software from Flash-drive and start the upgrade process.
4. Wait for the front panel of the symbols «b-YY», where YY - the percentage of Software upgrade process.
5. Remove Flash-drive from the USB port, without waiting for the upgrade process finished!
6. After updating, receiver will automatically reboot with the new Software version.